

Mode 1 channel	Mode 2 channel	8 bit channel	Value	Function	Type of control
9	9	7	0-95 96-127 128-159 128-142 143-144 145-159 160-191 160-174 175-176 177-191 192-223 192-206 207-208 209-223 224-255	Effects Open position (hole) Frost filter <i>Prism 1</i> forward rotation from max. to min. stop backward rotation from min. to max. <i>Prism 2</i> backward rotation from max. to min. stop forward rotation from min. to max. <i>Prism 3</i> forward rotation from max. to min stop backward rotation from min to max. <i>Prism 3 indexing</i>	step step proportional step proportional proportional step proportional proportional step proportional proportional
10	10	8	0-31 32-63 64-95 96-127 128-159 160-191 192-255	Static gobo Open Gobo 1 Gobo 2 Gobo 3 Gobo 4 Gobo 5 Gobo wheel rotation fro slow to fast	step step step step step step proportional
11	11	9	0-63 64-95 96-127 128-159 160-191 192-255	Rotating gobo Open Rot. gobo 1 (metal) Rot. gobo 2 (metal) Rot. gobo 3 (dichroic) Rot. gobo 4 (glass) No function	step step step step step step
12	12	10	0-127 128-190 191-192 193-255	Rotating gobo index,rotating gobo rotation Gobo indexing Forwards gobo rotation from fast to slow No rotation Backwards gobo rotation from slow to fast	proportional proportional step proportional
13	13	11	0 1-179 180-191 192-223 224-255	Iris Open Max.diameter to min.diameter Closed Pulse closing slow to fast Pulse opening fast to slow	step proportional step proportional proportional
14	14	12	0-85 86-170 171-255	Focus,multistep zoom Zoom 15° Zoom 21° Zoom 28°	proportional proportional proportional

Mode 1 channel	Mode 2 channel	8 bit channel	Value	Function	Type of control
15	15	13	0-31 32-63 64-95 96-127 128-159 160-191 192-223 224-255	Shutter, strobe Shutter closed No function (shutter open) Strobe-effect from slow to fast (max. 10 flashes/s) No function (shutter open) Pulse-effect in sequences No function (shutter open) Random strobe-effect from slow to fast No function (shutter open)	step step proportional step proportional step proportional step
16	16	14	0-255	Dimmer intensity Gradual adjustment of the dimmer intensity from 0 to 100%	proportional