

BEAM 250 XT - DMX PROTOCOL 8 bit

Channel	Value	Function	Type of control
1	0	Colour-wheel White/open	proportional
	10	Turquoise	proportional
	21	Red	proportional
	32	Cyan	proportional
	42	Light green	proportional
	53	Magenta	proportional
	64	Light blue	proportional
	74	Yellow	proportional
	85	Green	proportional
	96	Pink	proportional
	106	Blue	proportional
	117	Orange	proportional
	128-255	Rainbow effect from slow to fast	proportional
2	0-20	Effect-wheel Full open	step
	21-42	Colour temperature correction filter 3200 K	step
	43-63	Colour temperature correction filter 5600 K	step
	64-84	Magenta	step
	85-106	Cyan	step
	107-127	Yellow	step
	128-148	UV filter	step
	149-170	Gobo 1	step
	171-191	Gobo 2	step
	192-212	Beam reducer 1	step
	213-234	Beam reducer 2	step
	235-255	Beam reducer 3	step
	3	0-127	Shutter,stroke Open,From max.speed of fan to min. speed of fan
128-139		Open,Switch On the lamp,Reset	step
140-148		Closed	step
149		Closed in reverse position	step
150-219		Strobe-effect from slow to fast (max. 8 FPS)	proportional
220-229		Open position	step
230-239		Shutter is in half position of the beam,Lamp Off after 3 sec.	step
240-255		Open position	step
4	0	Dimmer Closed,Light is full Off	step
	1-126	Smooth dimming from black to full open	proportional
	127	Full open-sharp beam	step
	128-192	Smooth dimming from full open to black	proportional
	193-254	Smooth dimming from black to full open (frost light)	proportional
	255	Full open-frost(wash) light	step